

# Servomotorer

Fläns (mm)	Modell	Spänning (V)	Effekt (W)	Märkmoment / Maxmoment (Nm)	Märkvarvtal / Maxvarvtal (rpm)	PDF	DXF	
14,5	TS4861	24	3	0,0095/0,0285	3000/6000		DXF	
	TS4862		5	0,0159/0,0477			DXF	
	TS4864		10	0,032/0,096			DXF	
	TS4866		15	0,0477/0,1431			DXF	
19,5	TS4871	24	10	0,032/0,096	3000/6000	N/A	N/A	
	TS4872		16	0,051/0,153		N/A	N/A	
	TS4873		20	0,064/0,192		N/A	N/A	
	TS4875		30	0,096/0,288		N/A	N/A	
22	TS4631	24	13	0,031/0,094	3000/6000	N/A	N/A	
	TS4632		26	0,062/0,185		N/A	N/A	
	TS4633		40	0,095/0,285		N/A	N/A	
40	TS4601	100	30	0,095/0,29	3000/5000		DXF	
		200						
	TS4602	100	50	0,159/0,48			DXF	
		200						
	TS4603	100	100	0,318/0,95			DXF	
		200						
	TS4604	100	150	0,477/1,43			DXF	
		200						
60	TS4606	100	100	0,318/0,95	3000/5000		DXF	
		200						
	TS4607	100	200	0,64/1,91			DXF	
		200						
	TS4609	100	400	1,27/3,82			DXF	
200								
TS4610	200	600	1,91/5,73		DXF			
80	TS4611	100	200	0,64/1,91	3000/5000		DXF	
		200						
	TS4612	200	400	1,27/3,82			DXF	
		400						
TS4613	200	600	1,91/5,73		DXF			
TS4614	200	750	2,39/7,16		DXF			
100	TS4813	200	1000	3,3/9,9	3000/4500	N/A	N/A	
		400						
	TS4815	200	1500	4,8/14,4			N/A	N/A
		400						
	TS4817	200	2000	6,8/20,4			N/A	N/A
		400						
130	TS4833	200	1600	5,09/15,27	3000/4500	N/A	N/A	
		400						
	TS4836	200	3300	10,5/31,5			N/A	N/A
		400						
		200						

	TS4839	400	5000	15,9/47,7		N/A	N/A
180	TS4882	200	2000	9,4/23,5	2000/3000	N/A	N/A
		400					
	TS4884	200	4000	19,1/47,7		N/A	N/A
		400					
	TS4887	200	6000	28,6/71,5		N/A	N/A
		400					
TS4889	200	7500	35,8/89,5	N/A	N/A		
	400						
220	TS4927	200	11000	0,64/1,91	3000/5000	N/A	N/A
		400					
	TS4920	200	15000	1,27/3,82		N/A	N/A
		400					