

Singsyn resolver

| Modell | Storlek | Funktion | Spänning | Transformation ratio | Elektriskt fel | Vikt | | | |
|-----------------|---------|----------|----------------|----------------------|----------------|----------|----------|----------|---------|
| TS2223N1012E199 | S10 | 2X-VRX | AC 4Vrms 10kHz | 0.2 ± 10% | ± 60'Max | 0,023kg | | | |
| TS2223N1112E102 | | | AC 7Vrms 10kHz | | | | | | |
| TS2224N1012E199 | S15 | | AC 4Vrms 10kHz | | | ± 45'Max | 0,050kg | | |
| TS2224N1112E102 | | | AC 7Vrms 10kHz | | | | | | |
| TS2225N1012E199 | S21 | | AC 4Vrms 10kHz | | | | ± 30'Max | 0,076kg | |
| TS2225N1112E102 | | | AC 7Vrms 10kHz | | | | | | |
| TS2223N1013E199 | S10 | 3X-VRX | AC 4Vrms 10kHz | | 0.2 ± 10% | | | ± 45'Max | 0,023kg |
| TS2223N1113E102 | | | AC 7Vrms 10kHz | | | | | | |
| TS2224N1013E199 | S15 | | AC 4Vrms 10kHz | | | ± 30'Max | | | 0,050kg |
| TS2224N1113E102 | | | AC 7Vrms 10kHz | | | | | | |
| TS2225N1013E199 | S21 | | AC 4Vrms 10kHz | | | | ± 30'Max | | 0,076kg |
| TS2225N1113E102 | | | AC 7Vrms 10kHz | | | | | | |
| TS2223N1014E199 | S10 | 4X-VRX | AC 4Vrms 10kHz | 0.2 ± 10% | | | | ± 30'Max | 0,023kg |
| TS2223N1114E102 | | | AC 7Vrms 10kHz | | | | | | |
| TS2224N1014E199 | S15 | | AC 4Vrms 10kHz | | | ± 30'Max | | | 0,050kg |
| TS2224N1114E102 | | | AC 7Vrms 10kHz | | | | | | |
| TS2225N1014E199 | S21 | | AC 4Vrms 10kHz | | | | ± 30'Max | | 0,076kg |
| TS2225N1114E102 | | | AC 7Vrms 10kHz | | | | | | |